

Kodak ScanMate i940 Scanner

Capture, manage, and distribute information with ease and speed The perfect compact desktop and mobile scanning teammate

If you need to scan, store, manage, and send information to various locations and people within your organisation with ease, you need a **Kodak ScanMate** i940 Scanner. It moves your valuable information from paper into your workflow quickly and intuitively.

To make information capture and distribution even more foolproof, the **ScanMate** i940 Scanner uses Smart Touch functionality – so the push of one button replaces complicated multi-step scanning processes. Easily create email attachments, image files, and searchable PDFs – and send your documents securely to the Cloud, so they can be accessed anywhere, anytime.

Powered via USB, the very compact i940 Scanner also lets you scan on-the-go. It's compact but delivers big impact.

Open up new scanning, information capture, and sharing possibilities with the freedom and power of the **Kodak ScanMate** i940 Scanner.



10 ways the **Kodak ScanMate** i940 Scanner does more in less space

Saves time

• Smart Touch performs multiple-step scanning and organising operations automatically

Saves space

Compact, highly portable scanner takes up less desk space

Scans anywhere

 USB-powered to provide the power of a desktop scanner with the flexibility of a mobile scanner

Plays well with others

Compatible with most scanning software

Creates sharp images – even better than many originals

 Perfect Page document imaging is built in—for great images with bright colours and crisp text

Scans many sizes and weights

• 20-sheet automatic document feeder even handles business cards, ID cards, and embossed hard cards

Keeps contacts up to date

• Easily edit and synchronise business card information in your contact application(s)

Delivers peace of mind

• Three-year limited warranty on a wellmade, proven scanner

Lets you remotely manage

 Available Kodak Asset Management Software for remote management of select Kodak Scanners on your network, including the i940 Scanner (Visit kodakalaris.com/go/ AssetManagement to learn more)

Kodak ScanMate i940 Scanner



Technical specifications	
Software Support	Windows bundled software: TWAIN, ISIS, WIA drivers; Smart Touch; and NewSoft Presto! BizCard, Kodak Capture Pro Software Limited Edition. Fully supported by Kodak Capture Pro Software and Kodak Asset Management Software (Windows only)
	Mac bundled software: NewSoft Presto! Page Manager; NewSoft Presto! BizCard X press; TWAIN driver (available web download only)
Supported Operating Systems	Windows XP SP3 (32-bit and 64-bit), Windows Vista SP1 (32-bit and 64-bit), Windows 7 SP1 (32-bit and 64-bit), Windows 8 (32-bit and 64-bit), Windows 8.1 (32-bit and 64-bit), Windows 10 (32-bit and 64-bit), Linux Ubuntu 12.04 (LTS)*; Mac OS v.10.8, 10.9, 10.10*; Kofax certified
Recommended Daily Volume	Up to 1,000 pages per day
Throughput Speeds (portrait, letter size)	When AC-powered: black and white/greyscale: up to 20 ppm/40 ipm at 200 dpi; colour: up to 15 ppm/30 ipm at 200 dpi When USB-powered: black and white/greyscale/colour: up to 8 ppm/16 ipm at 200 dpi (Throughput speeds may vary depending on your choice of driver, application software, operating system, and host computer)
Optical Resolution	600 dpi
Max./Min. Document Size	216 mm x 1524 mm/80 mm x 52 mm
Paper Thickness and Weight	30 to 398 g/m ² paper; ID card and embossed hard card thickness: up to 1.25 mm Note: with document feeding set for "card" scanning, paper thickness can be up to 995 g/m ²
Feeder	ADF: up to 20 sheets of 80 g/m² paper The feeder can handle a variety of small documents, such as identification cards, business cards, insurance cards, and embossed hard cards
Connectivity	USB 2.0, USB 3.0 compatible
Imaging Features	Perfect Page Scanning, iThresholding, automatic image straightening (deskew), auto cropping, image rotation, electronic colour dropout, dual stream scanning, image merge, image edge fill, content-based blank page removal, automatic brightness and contrast
File Format Outputs	Single and multi-page TIFF, JPEG, RTF, BMP, single and multi-page PDF, searchable PDF
Warranty	3 years (Advanced Unit Replacement)
Electrical Requirements	AC power supply and/or USB power via USB connector to the host computer
Environmental Factors	Energy Star qualified scanner
Dimensions	Height: 78 mm with tray closed Width: 289 mm with tray closed Depth: 107 mm with tray closed Weight: 1.3 kg without power adapter
	* Smart Touch functionality is not supported on these Operating Systems.

The Kodak ScanMate i940 Scanner is compatible with gDocScan and Microsoft SharePoint applications.

Uvoznik za Slovenijo:

e-DISTI d.o.o., Litijska cesta 259, 1261 Ljubljana-Dobrunje e-mail: info@e-disti.com, www.mojskener.si

Uvoznik za Hrvatsku:

e-DISTI d.o.o., Karamanov prilaz 2, 10000 Zagreb e-mail: prodajahr@e-disti.com, www.alaris.com.hr

Uvoznik za Srbiju:

e-DISTI d.o.o., Učitelja Miloša Jankovića br.2, 11160 Beograd - Zvezdara e-mail: zoran@e-disti.com; www.kodak-skener.rs



To learn more: www.kodakalaris.com/go/i940



For further information, please see how to contact us at: http://www.kodakalaris.com/go/dicontact

Kodak alaris









© 2016 Kodak Alaris Inc. The Kodak trademark and trade dress are used under license from Eastman Kodak Company. Specifications are subject to change without notice. 10/16 · DM110-16

